

Applicable Requirements: ANSI/UL 1017 CSA C22.2 No.243



Complies with NFPA 77 "Recommended Practice on Static Electricity'



Characteristics













Stainless General

SD Tools &

HEPA. Included

High Filtration Efficiency Unit

LIFETIME

Brushless Motor Available

- Ideal for housekeeping and general cleaning
- Complies with NFPA 652 paragraph 8.4.2.2.1.7 and NFPA 654 paragraph 8.4.3.7 (1) to (7)
- Protected against ingress of dust
- HEPA filter with an efficiency of 99.995% at 0.3 micron. Tested IEST-RP-CC001. H14 by MPPS method as per EN 1822 and OSHA compliant. All of our HEPA vacuum systems are aerosol leak tested before leaving our facility - included
- Heavy duty 2-stage by-pass motor
- Longer life brushless motor available. Always with 2 x H14 HEPA filters
- For dry recovery only
- A package of the disposable conductive "wet" recovery bags is included with the vacuum cleaner
- Stainless steel tank Type 430 fits any application
- Filter blockage indicator light
- Includes a complete static dissipative tool kit

Specifications

2D-10 (4W) HEPA ORDLOC-652 W/3D TOOL KIT	113185A-3D	113185A-BL3D
Model Name	2D-10 (4W) HEPA ORDLOC-652 W/3D TOOL KIT	2D-10 (4W) HEPA ORDLOC-652 W/BRUSHLESS MOTOR W/3D TOOL KIT
Type (Powerhead)	Electric	Electric
Tension	120 V	120 V
Frequency	60 Hz	60 Hz
Phase	Single	Single
Wattage	1207 W	1100 W
Power	1.6 HP	1.5 HP
Amperage	10.5 A	13 A
Air Flow	110 CFM	127 CFM
Vacuum Pressure	107 " H ₂ 0	89 " H ₂ 0
Sound Level	75 dB(A)	75 dB(A)
Type of Power Outlet	120V	120V
Suction Inlet Port	60 mm	60 mm
Cart Type	4 Wheel Dolly (4W)	4 Wheel Dolly (4W)
Dry Recovery - Disposable Filter Bag	5 gal.	5 gal.
Length	17 "	17 "
Width	17 "	17 "
Height	34 "	35 "
Cord Length	35 ft.	35 ft.

Please note that specifications are subject to change without notice

Use only recommended tools & accessories



Upstream HEPA Filter - Included



Conductive Recovery Bags - included



3D Tool Kit for 60 mm suction inlet - included



Optional 3D Tools



Longer Life Brushless Motor Available (always with 2 x H14 HEPA filters)