

U.S. Headquarters

Tiger-Vac Inc.
11 SW 12th Ave #112
Dania, FL 33004
USA

Tel: 1-800-668-4437 (954-925-3625)
Fax: 1-800-668-4439 (954-925-3626)
Website: <http://www.tiger-vac.com>
Email: sales@tiger-vac.com

International Headquarters

Tiger-Vac International Inc.
2020 Dagenais Blvd. Ouest
Laval, Quebec
Canada H7L 5W2

Tel: (450-625-0099)
Fax: (450-625-3388)
Website: <http://www.tiger-vac.com>
Email: sales@tiger-vac.com



Applicable requirements :
Standard(s) for Electric Vacuum Cleaning
Machines and Blower Cleaners (UL-1017)



Pharma
Applications



Cleanroom
Compatible



ULPA -
Included



Safe
Containment



Stainless
Steel
General



Low Noise



Dry Recovery



High Filtration
Efficiency Unit



HEPA -
Included

Specifications For CR-1000 (CV) SERIES

Name	Part Number	Tension	Frequency	Phase	Wattage	Power	Amperage	Air Flow	Vacuum Pressure	Type of Power Outlet
CR-1000 (CV)	111993A	120 V	60 Hz	Single	1000 W	1.3 HP	8.3 A	96 CFM	99 " H ₂ O	120V
	Dimensions: H26" x W16" x L23" Weight: 24 lb. Sound Level: 60 dB(A)									
Description: With safe containment canister, without ULPA filter protector housing										
CR-1000 (CV) WITH ULPA PROTECTOR	111994A	120 V	60 Hz	Single	1000 W	1.3 HP	8.3 A	96 CFM	99 " H ₂ O	120V
	Dimensions: H26" x W16" x L23" Weight: 24 lb. Sound Level: 60 dB(A)									
Description: With safe containment canister and ULPA filter protector housing										

Please note that specifications are subject to change without notice

Technical Sheet For CR-1000 (CV) SERIES

ULPA FILTER - Included	
Part #	Description
212304	ULPA FILTER (U15)
ULPA FILTER HOUSING PROTECTOR KIT - Optional	
Part #	Description
214860	ULPA FILTER PROTECTOR/HOUSING KIT FOR MODEL CR-1 (ULPA FILTER NOT INCLUDED)
FILTERS AND ACCESSORIES - Included	
Part #	Description
212503T	PTFE LAMINATED MAIN FILTER ASSEMBLY WITH BLACK PLASTIC RING
SAFE CONTAINMENT CANISTER - Included	
Part #	Description
212522	SAFE CONTAINMENT CANISTER ASSEMBLY
Ø1.25" (Ø32mm) TOOL KITS - Optional	
Part #	Description
323600	TOOL KIT #1(STANDARD TYPE) FOR MODEL CR-1000
323602	ESD SAFE TOOL KIT #2 FOR CR-1000
323604	AUTOCLAVABLE TOOL KIT #3 FOR MODEL CR-1000
Ø1.25" (Ø32mm) STANDARD TOOLS AND ACCESSORIES - KIT #1 - Optional	
Part #	Description
323606	SUCTION HOSE ASSEMBLY (STANDARD TYPE) 1.25"(32mm)x8'(2.4m) FOR MODEL CR-1000

323504A	TELESCOPIC EXTENSION WAND FOR MODEL CR-1 (REPLACEMENT FOR MODEL T1), PLASTIC
323508	FLOOR TOOL 1.25"(32mm) x 14"(36cm), FOR AS-5 AND CR-1, BLACK PLASTIC
323510	CREVICE TOOL FOR AS-5 AND CR-1 1.25"(32mm)x8"(20.3cm)
323514	DUSTING BRUSH FOR AS-5 AND CR-1 1.25"(32mm)x3"(76mm)
323512	UPHOLSTERY TOOL FOR AS-5 AND CR-1 1.25"(32mm)x5"(13cm)
323600	TOOL KIT #1(STANDARD TYPE) FOR MODEL CR-1000

Ø1.25" (Ø32mm) ESD SAFE TOOLS AND ACCESSORIES - KIT #2 - Optional

Part #	Description
323316	MICRO TOOL KIT, Ø1.25"(32mm), ESD* SAFE PLASTIC
323608	SUCTION HOSE ASSEMBLY, ESD SAFE, 1.25"(32mm)x8'(2.4m) FOR MODEL CR-1000
323331	STAINLESS STEEL WANDS 1.25" 32cm (SET OF 2) - ONE CURVED AND ONE STRAIGHT
323318A	UTILITY FLOOR TOOL, Ø1.25"(Ø32mm) x 12"(30cm), STATIC CONDUCTIVE PLASTIC w/CONDUCTIVE NYLON BRISTLES
323313A	CREVICE TOOL, 1.25"(32mm) x 8"(20cm), BLACK, ESD SAFE PLASTIC w/HOLE FOR BUTTON LOCK
323312A	ROUND BRUSH, 1.25"(32mm) x 3"(7.5cm), ESD SAFE PLASTIC, WITH HOLE FOR BUTTON LOCK
323321A	ROUND TOOL, WITH RUBBER BLADES, Ø1.25"(32mm), ESD SAFE PLASTIC
323314A	UPHOLSTERY FLAT TOOL, 1.25"(32mm) x 5"(13cm), ESD SAFE PLASTIC
323602	ESD SAFE TOOL KIT #2 FOR CR-1000

Ø1.25" (Ø32mm) AUTOCLAVABLE TOOLS AND ACCESSORIES - KIT #3 - Optional

Part #	Description
323462	EPDM SUCTION HOSE ASSEMBLY (AUTOCLAVABLE) 1.25"(32mm)x8'(2.4m) FOR MODEL CR-1000
323331	STAINLESS STEEL WANDS 1.25" 32cm (SET OF 2) - ONE CURVED AND ONE STRAIGHT
323412	FLOOR TOOL ASSEMBLY, AUTOCLAVABLE, 1.25"(32mm) x 12"(30cm), STAINLESS STEEL w/WHITE NITRILE BLADES
323413	CREVICE TOOL, AUTOCLAVABLE, Ø1.25"(32mm)x10"(25.4cm) -STAINLESS STEEL
323565	CONICAL NOZZLE w/CURVED TIP w/SS CONNECTOR INSTALLED 1.25"(32mm)x10"(25cm), CLEAR FOODGRADE SILICONE
323604	AUTOCLAVABLE TOOL KIT #3 FOR MODEL CR-1000